



INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁶ : G08B 13/14	A1	(11) International Publication Number: WO 99/65002 (43) International Publication Date: 16 December 1999 (16.12.99)
--	-----------	---

(21) International Application Number: PCT/US99/12640

(22) International Filing Date: 8 June 1999 (08.06.99)

(30) Priority Data:
09/094,261 9 June 1998 (09.06.98) US

(71) Applicant: MOTOROLA INC. [US/US]; 1303 East Algonquin Road, Schaumburg, IL 60196 (US).

(72) Inventors: EBERHARDT, Noel, H.; 21407 Kryzich Place, Cupertino, CA 95014 (US). GHAEM, Sanjar; 107 Ash Street, Palatine, IL 60067 (US).


(74) Agents: HUGHES, Terri, S. et al.; Motorola Inc., Intellectual Property Dept., 1303 East Algonquin Road, Schaumburg, IL 60196 (US).

(81) Designated States: AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, CA, CH, CN, CU, CZ, DE, DK, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MD, MG, MK, MN, MW, MX, NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TR, TT, UA, UG, UZ, VN, YU, ZW, ARIPO patent (GH, GM, KE, LS, MW, SD, SL, SZ, UG, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GW, ML, MR, NE, SN, TD, TG).

Published

With international search report.

(54) Title: RADIO FREQUENCY IDENTIFICATION TAG HAVING AN ARTICLE INTEGRATED ANTENNA



(57) Abstract

A radio frequency identification tag (14) utilizes an antenna (22) formed in association with, and thus integral to, an article, package, package container, label and/or identification badge (10). In a preferred embodiment, a radio frequency identification tag circuit chip assembly (12) is secured to the article (10) and is electrically coupled to the antenna (22) formed on the article (10). Printing a conductive pattern on the article using conductive ink forms a preferred antenna.

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece			TR	Turkey
BG	Bulgaria	HU	Hungary	ML	Mali	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MN	Mongolia	UA	Ukraine
BR	Brazil	IL	Israel	MR	Mauritania	UG	Uganda
BY	Belarus	IS	Iceland	MW	Malawi	US	United States of America
CA	Canada	IT	Italy	MX	Mexico	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NE	Niger	VN	Viet Nam
CG	Congo	KE	Kenya	NL	Netherlands	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NO	Norway	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	NZ	New Zealand		
CM	Cameroon			PL	Poland		
CN	China	KR	Republic of Korea	PT	Portugal		
CU	Cuba	KZ	Kazakhstan	RO	Romania		
CZ	Czech Republic	LC	Saint Lucia	RU	Russian Federation		
DE	Germany	LI	Liechtenstein	SD	Sudan		
DK	Denmark	LK	Sri Lanka	SE	Sweden		
EE	Estonia	LR	Liberia	SG	Singapore		

- 1 -

RADIO FREQUENCY IDENTIFICATION TAG HAVING AN ARTICLE
INTEGRATED ANTENNA

5

Cross-Reference to Related Applications

10 The present application is related to the following commonly-
assigned prior U.S. patent applications: Ted Geiszler et al., "Remotely
powered electronic tag and associated exciter/reader and related
method," serial number 08/540,813, filed 11 October 1995, attorney
docket number IND00701; Victor Allen Vega et al., "Radio frequency
15 identification tag system using tags arranged for coupling to ground,"
serial number 09/031,848, filed 27 February 1998, attorney docket
number IND10153; Victor Allen Vega et al., "Radio frequency
identification tag arranged for magnetically storing tag state information,"
serial number 09/041,480, filed 12 March 1998, attorney docket number
20 IND10146; and Victor Allen Vega, "Radio frequency identification tag with
a programmable circuit state," serial number 09/045,357, filed 20 March
1998, attorney docket number IND10174, the disclosures of which prior
applications are hereby expressly incorporated by reference, verbatim and
with the same effect as though such disclosures were fully and completely
25 set forth herein.

Field of the Invention

The present invention relates generally to the field of radio-
frequency identification tags including, but not limited to, radio frequency
30 identification tags having an article integrated antenna.

Background of the Invention

Radio frequency identification tags and radio frequency
identification tag systems are known, and find numerous uses. For
35 example, radio frequency identification tags are frequently used for

- 2 -

personal identification in automated gate sentry applications protecting secured buildings or areas. Information stored on the radio frequency identification tag identifies the person seeking access to the secured building. A radio frequency identification tag system conveniently
5 provides for reading the information from the radio frequency identification tag at a small distance using radio frequency (RF) data transmission technology. Most typically, the user simply holds or places the radio frequency identification tag near a base station that transmits an excitation signal to the radio frequency identification tag powering circuitry contained
10 on the radio frequency identification tag. The circuitry, responsive to the excitation signal, communicates the stored information from the radio frequency identification tag to the base station, which receives and decodes the information. In general, radio frequency identification tags are capable of retaining and, in operation, transmitting a substantial
15 amount of information – sufficient information to uniquely identify individuals, packages, inventory and the like.

A typical technology for powering and reading a radio frequency identification tag is inductive coupling or a combination of inductive power coupling and capacitive data coupling. Inductive coupling utilizes a coil
20 element in the radio frequency identification tag. The coil element is excited (or "energized") by an excitation signal from the base station to provide power to the radio frequency identification tag circuitry. The radio frequency identification tag coil, or a second tag coil, may be used to transmit and receive the stored information between the radio frequency
25 identification tag and the base station. Radio frequency identification tags relying on inductive coupling are sensitive to orientation of the radio frequency identification tag with respect to the base station since the field created by the excitation signal must intersect the coil element at substantially a right angle for effective coupling. Read ranges for
30 inductively coupled devices are generally on the order of several centimeters. Longer read distances are desirable, and for certain applications, such as electronic animal identification, baggage tracking, parcel tracking and inventory management applications, are necessary.

Another technology for powering and reading radio frequency
35 identification tags is electrostatic coupling such as employed in the radio

- 3 -

frequency identification tag systems and radio frequency identification tags disclosed in the above referenced applications. These systems advantageously provide for substantially increased read/write distances over those available in the prior art. Another advantage derived from the use of the systems and tags therein disclosed is that the user need not bring the radio frequency identification tag in close proximity to a base station or to substantially orient the tag with respect to the base station. It is therefore possible to incorporate the antenna elements of the base station into, for example, a doorway or a vestibule, a package conveyer or an article sorting system, and to energize the tag and read the tag information at a greater distance.

To couple either the inductive or electrostatic signals between the base station and the radio frequency identification tag, the tag necessarily includes an antenna having at least one and frequently two antenna elements. Typically, a tag circuit chip and the antenna are electrically coupled and bonded to a tag substrate. The tag dimensions, governed by the tag substrate dimensions, are typically maintained fairly small. Therefore, the antenna is generally size limited. A smaller antenna, however, adversely affects read ranges. Also, the antenna is necessarily formed co-planar with the tag substrate potentially making the tag orientation sensitive. Because it is undesirable and generally impractical to make the radio frequency identification tag larger, effective antenna size remains limited. And, the typical flat tag design also limits the antenna to a flat, orientation sensitive configuration.

To date radio frequency identification tags have been manufactured as self-contained units, i.e., tag circuit chip, antenna and substrate as a singular package. Therefore, not only has the size and configuration of the antenna posed problems with performance of the radio frequency identification tag, the antenna contributes significantly to the cost of a completed tag.

Applications for radio frequency identification tags include personal identification badges, article and/or package identification tags, and electronic article surveillance tags. In many of these applications, the identification badge, the article and/or package is substantially larger than the radio frequency identification tag used to provide the identifying

- 4 -

information. However, the size of the identification badge, article or package has not offered an opportunity for increasing the size or reducing the orientation sensitivity of the antenna of a self-contained radio frequency identification tag.

5 Thus, there is a need for an improved radio frequency identification tag.

Brief Description of the Drawings

10 Preferred exemplary embodiments of the invention are illustrated in the accompanying drawings in which like reference numerals represent like parts throughout.

FIG. 1 is an exploded assembly view of a radio frequency identification tag in accordance with a preferred embodiment of the present invention.

15 FIG. 2 is a cross-section view taken along line 2-2 of FIG. 1.

FIG. 3 is a perspective view of a radio frequency identification tag circuit chip assembly partially broken away to reveal a conductor element formed therein.

FIG. 4 is a cross-section view taken along line 4-4 of FIG. 3.

20 FIG. 5 is an exploded assembly view of a radio frequency identification tag in accordance with a preferred embodiment of the present invention.

FIG. 6 is a cross-section view taken along line 6-6 of FIG. 5.

25 FIG. 7 is a perspective view of a radio frequency identification tag circuit chip assembly.

FIG. 8 is a cross-section view taken along line 8-8 of FIG. 7.

FIG. 9 is an exploded assembly view of a radio frequency identification tag in accordance with an alternate preferred embodiment of the present invention.

30 FIG. 10 is a cross-section view taken along line 10-10 of FIG. 9.

FIG. 11 is a cross-section view similar to the view of FIG. 10 and illustrating an alternate preferred embodiment of the present invention.

35 FIG. 12 is a cross-section view of a radio frequency identification tag in accordance with an alternate preferred embodiment of the present invention.

- 5 -

FIG. 13 is a cross-section view of a radio frequency identification tag in accordance with an alternate preferred embodiment of the present invention.

5 FIG. 14 is a cross-section view of a radio frequency identification tag in accordance with an alternate preferred embodiment of the present invention.

FIG. 15 is a perspective view of an unassembled package container in accordance with a preferred embodiment of the present invention.

10 FIG. 16 is a perspective view of an assembled package container in accordance with a preferred embodiment of the present invention.

Detailed Description of the Preferred Embodiments

Radio frequency identification tags in accordance with preferred
15 embodiments of the present invention utilize an antenna formed in association with, and thus integral to, an article, package, package container, label and/or identification badge ("article"). In a preferred embodiment of the present invention, a radio frequency identification tag circuit chip assembly is secured to the article and is electrically coupled to
20 the antenna formed on the article. Printing a conductive pattern on the article using conductive ink forms a preferred antenna.

Referring to FIG. 1 of the drawings, shown in exploded assembly view radio frequency identification tag 14 includes an article 10 and a radio frequency identification tag circuit chip assembly ("chip assembly")
25 12. Article 10 is shown generally as a substrate 16 formed from a sheet of material having a first surface 18 and a second surface 20. It will be appreciated that substrate 16 may form the basis for a personal identification badge, a label, a package container (such as a box or envelope) and the like. Moreover, the substrate material may be any
30 suitable material for the particular application such as plastic (including polyester and metalized polyester material), paper, synthetic paper, reinforced paper, cardboard, synthetic paper coated cardboard and the like. As will be described with respect to alternate preferred embodiments of the invention below, a radio frequency identification tag circuit chip may
35 be attached directly to a substrate arranged with an integrally formed

- 6 -

antenna. The arrangement of chip assembly 12 advantageously provides manufacturing convenience since many chip assemblies may be produced in high volume using automated techniques. The chip assemblies 12 are relatively small, on the order of 1 – 2 cm square, and thus easier to store, ship and handle versus the article to which it is attached. Moreover, chip assembly 12, as will be described, provides for a substantially simplified way of attaching the radio frequency identification tag circuit chip to an article, and concomitantly coupling the same to the integrally formed antenna.

Formed on first surface 18 is an antenna 22 including a first antenna element 24 and a second antenna element 26. Each of first antenna element 24 and second antenna element 26 are formed from a conductive material that is bonded or otherwise secured to, and thus integral to, article 10. Most preferably, each of first antenna element 24 and second antenna element 26 are formed by printing, using a suitable printable conductive medium. For example, a carbon/graphite based conductive ink forms an effective antenna 22 when printed onto paper and/or cardboard. Synthetic and coated papers may alternatively be used, but at added cost. Silver and other precious metal inks may be used particularly for printing on plastic materials, but are less preferred due to higher material costs. Antenna 22 is shown to have a generally broken "H" shape as would be suitable for use in an electrostatic signal application. It will be appreciated that other patterns more suitable to, for example, inductive coupling may be printed without departing from the fair scope of the present invention. Each of first antenna element 24 and second antenna element 26 include at generally the center of the broken "H" pattern, respectively, a first coupling region 28 and a second coupling region 30. Most preferably, antenna 22 may be made substantially larger than in traditional radio frequency identification tag construction, approaching the surface area of surface 18. Each of first coupling region 28 and second coupling region 30 includes a conductive pad area for electrically coupling to chip assembly 12 by means of a layer 34 of anisotropic adhesive (FIG. 2).

A preferred anisotropic adhesive is 3M 9703 adhesive available from 3M Corporation. The preferred adhesive is anisotropic in that it

- 7 -

conducts in the "z" or vertical direction only (FIG. 1). The adhesive is manufactured to include metallic coated micro-sized pellets in an adhesive substrate that make electrical contact from the top surface to the lower surface of adhesive layer 34. Electrical contact is not made in either of the "x" or "y" directions, i.e., the plane of adhesive layer 34. Thus, adhesive may be applied in a complete layer without shorting across adjacent conductors.

With reference then to FIG. 2 and further reference to FIG. 3 and FIG. 4, chip assembly 12 includes a substrate 36 on which a conductive pattern 37 including a first conductive member 38 and a second conductive member 40 is formed. Substrate 36 is preferably a thin, flexible sheet of paper, plastic, synthetic paper or other similar material with paper being a preferred, low cost substrate material. Each of first conductive member 38 and second conductive member 40 are preferably formed by printing conductive pattern 37 onto substrate 36 using a suitable printable conductive medium. Suitable conductive inks include carbon/graphite bearing inks, precious metal bearing inks and the like selected for compatibility with substrate 36.

As seen in FIG. 3, a preferred conductive pattern 37 formed by first conductive member 38 and second conductive member 40 is a broken "H" providing a substantial area for coupling to antenna 22 and providing a first chip coupling region 42 and a second chip coupling region 44, respectively. Secured to substrate 36 and coupled to first and second coupling regions 42 and 44 by means of layer 34 is a radio frequency identification tag circuit chip ("circuit chip") 46.

In a read/write embodiment, circuit chip 46 may be advantageously constructed from a TEMIC e5550 circuit chip (available from Temic North America, Inc., Basking Ridge, New Jersey). In a read only embodiment, an Indala I341 circuit chip (available from Motorola Indala Corporation, San Jose, California) may be used. Circuit chip 46 is formed with a first conductive pad 48 and a second conductive pad 50 arranged for coupling to conductive pattern 37. As shown, first conductive pad 48 and second conductive pad 50 are "bumped" pads. That is, they project outwardly from the surface of circuit chip 46 in contrast to "surface" pads, which are formed substantially coplanar with the outer surface of a circuit chip.

- 8 -

When secured to substrate 36, first conductive pad 48 contacts first chip coupling region 42 and conductive pad 50 contacts second chip coupling region 44 providing an operable, electrical coupling therebetween. A small region 52 of layer 34 is slightly compressed between circuit chip 46 and substrate 36 forming a strong mechanical bond of circuit chip 46 to substrate 36. No particular preference exists for the use of bumped pads, and either bumped pads, surface pads or recessed pads (i.e., conductive pads formed recessed into an outer surface of circuit chip 46) may be selected based upon cost and the particular application.

As is appreciated from the foregoing discussion, and in accordance with a preferred embodiment of the present invention, radio frequency identification tag 14 is formed by joining circuit chip assembly 12 to article 10 having an integrally formed antenna 22. The only size limitation for antenna 22 is thus the available non-metallic and/or non-conductive surface area of article 10. In this manner, a substantially larger antenna than would otherwise be possible on a traditional radio frequency identification tag may be achieved. The direct benefits included increased read distances and potentially reduce orientation sensitivity. Additionally, antenna 22 may be printed on the article using inexpensive carbon/graphite bearing conductive ink, and may be formed on a number of non-coplanar and/or non-parallel surfaces of article 10 thereby reducing orientation sensitivity. Thus, the performance improvements are achieved at reduced costs.

With reference now to FIG. 5 of the drawings, shown in exploded assembly view a radio frequency identification tag 114 includes an article 110 and a radio frequency identification tag circuit chip assembly ("chip assembly") 112. Article 110 is shown generally as a substrate 116 formed from a sheet of material having a first surface 118 and a second surface 120. It will be appreciated that substrate 116 may form the basis for a personal identification badge, a label, a package container (such as a box or envelope) and the like. Moreover, the substrate material may be any suitable material for the particular application such as paper, plastic (including polyester and metalized polyester material), synthetic paper, reinforced paper, cardboard, synthetic paper coated cardboard and the

- 9 -

like, with paper providing a suitable, low cost and thus preferred substrate material.

5 Formed on first surface 118 is an antenna 122 including a first antenna element 124 and a second antenna element 126. Each of first antenna element 124 and second antenna element 126 are a formed from a conductive material that is bonded or otherwise secured to, and thus integral to, article 110. Most preferably, each of first antenna element 124 and second antenna element 126 are formed by printing, using a suitable printable conductive medium. For example, a carbon/graphite based
10 conductive ink forms an effective antenna 122 when printed onto paper, cardboard, coated cardboard and/or synthetic paper. Silver and other precious metal inks may be used particularly for printing on plastic materials, but are less preferred due to higher material costs. Antenna 122 is shown to have a generally broken "H" shape as would be suitable
15 for use in an electrostatic signal application. It will be appreciate that other patterns more suitable to, for example, inductive coupling may be printed without departing from the fair scope of the present invention. Each of first antenna element 124 and second antenna element 126 include at generally the center of the broken "H" pattern, respectively, a
20 first coupling region 128 and a second coupling region 130. Most preferably, antenna 122 may be made substantially larger than in traditional radio frequency identification tag construction, approaching the surface area of surface 118. Each of first coupling region 128 and second coupling region 130 includes a conductive pad area for electrically
25 coupling to chip assembly 112 by means of adhesive layer 134 and adhesive layer 135 (FIG. 6). Since adhesive layer 134 and adhesive layer 135 are separate from each other on chip assembly 112, an isotropic adhesive may be used. A preferred isotropic adhesive is #8001 available from Adhesives Research, Inc.

30 With reference then to FIG. 6 and further reference to FIG. 7 and FIG. 8, chip assembly 112 includes a substrate 136 onto which a conductive pattern 137 including a first conductive member 138 and a second conductive member 140 is formed. Substrate 136 is preferably a thin, flexible sheet of paper, plastic, synthetic paper or other similar
35 material. Each of first conductive member 138 and second conductive

- 10 -

member 140 are preferably formed by printing conductive pattern 137 onto substrate 136 using a suitable printable conductive medium. Suitable conductive inks include carbon/graphite bearing inks, precious metal bearing inks and the like selected for compatibility with substrate 136.

As seen in FIG. 7, a preferred conductive pattern 137 formed by first conductive member 138 and second conductive member 140 is a broken "H" providing a substantial area for coupling to antenna 122 and providing a first chip coupling region 142 and a second chip coupling region 144, respectively. Secured to substrate 136 using a suitable adhesive, such as an epoxy adhesive, is a radio frequency identification tag circuit chip ("circuit chip") 146.

In a read/write embodiment, circuit chip 146 may be advantageously constructed from the TEMIC e5550 circuit chip, and in a read only embodiment, from the Indala I341 circuit. Circuit chip 146 is formed with a first conductive pad and a second conductive pad (not shown) for coupling to an antenna, such as antenna 22. The first and second conductive pads may be "surface" pads, "recessed" pads, or "bumped" pads as desired. Circuit chip 146 is secured to substrate 136 with the first and second conductive pads facing away from substrate 136. Once secured to substrate 136, a layer of conductive adhesive 148 electrically couples the first conductive pad to first chip coupling region 142 and a layer of conductive adhesive 150 electrically couples the second conductive pad to second chip coupling region 44 providing an operable, electrical coupling therebetween.

Similar to radio frequency identification tag 14, radio frequency identification tag 114 is formed by joining circuit chip assembly 112 to article 110 having an integrally formed antenna 122. Thus, the only size limitation for antenna 122 is the available non-metallic, non-conductive surface area of article 10. In this manner, a substantially larger antenna than would otherwise be possible to provide on a traditional radio frequency identification tag may be achieved. Also, orientation sensitivity may be reduced by forming antenna 122 on non-parallel surfaces. The direct benefits included increased read distances, potentially reduce orientation sensitivity and reduced cost.

- 11 -

A plurality of chip assemblies 12 or 112 may be prepared and secured to a transport medium (not shown) by means of layer 34 and layer 134 and layer 135, respectively. The transport medium permits easy removal of individual chip assemblies therefrom, and may be a sheet or roll of material. From the transport medium, a chip assembly may be removed and then secured to an article. For example, in an inventory and packaging operation, as packages are assembled, chip assemblies may be applied as necessary for tracking such packages.

Referring now to FIG. 9 of the drawings, shown in exploded assembly view, radio frequency identification tag 214 is formed by directly joining a radio frequency identification tag circuit chip ("circuit chip") 246 to an article 210 having an integrally formed antenna 222. Article 210 is shown generally as a substrate 216 formed from a sheet of material having a first surface 218 and a second surface 220. It will be appreciated that substrate 216 may form the basis for a personal identification badge, a label, a package container (such as a box or envelope) and the like. Moreover, the substrate material may be any suitable material for the particular application such as paper, plastic (including polyester and metalized polyester material), synthetic paper, reinforced paper, cardboard, coated cardboard and the like.

Formed on first surface 218 is an antenna 222 including a first antenna element 224 and a second antenna element 226. Each of first antenna element 224 and second antenna element 226 are formed from a conductive material that is bonded or otherwise secured to, and thus integral to, article 210. Most preferably, each of first antenna element 224 and second antenna element 226 are formed by printing, using a suitable printable conductive medium. For example, a carbon/graphite based conductive ink forms an effective antenna 222 when printed onto synthetic paper and/or synthetic paper coated cardboard. Silver and other precious metal inks may be used particularly for printing on plastic materials, but are less preferred due to higher material costs. Antenna 222 is shown to have a generally broken "H" shape as would be suitable for use in an electrostatic signal application. It will be appreciated that other patterns more suitable to, for example, inductive coupling may be printed without departing from the fair scope of the present invention. Each of first

- 12 -

antenna element 224 and second antenna element 226 include at generally the center of the broken "H" pattern, respectively, a first coupling region 228 and a second coupling region 230. Most preferably, antenna 222 may be made substantially larger, approaching the surface area of surface 218 of article 210, than in traditional radio frequency identification tag construction.

Referring now to FIG. 10, circuit chip 246 is bonded to article 210 by means of a layer 234 of an anisotropic adhesive. In a read/write embodiment, circuit chip 146 may be advantageously constructed from the TEMIC e5550 circuit, and in a read only embodiment, from the Indala 1341 circuit. Circuit chip 246 is formed with a first conductive pad 248 and a second conductive pad 250 for coupling to antenna 222. As shown, first conductive pad 248 and second conductive pad 250 are "bumped" pads, however, surface pads, recessed pads, or other suitable conductive pads formed on circuit chip 246 may be used. Conductive pad 248 and conductive pad 250 are arranged for respectively electrically contacting first chip coupling region 242 and second chip coupling region 244 providing an operable, electrical coupling therebetween. A small region 252 of layer 234 is slightly compressed between circuit chip 246 and substrate 216 forming a strong mechanical bond. A protective sheet (not shown) may then be applied over circuit chip 246 and layer 234.

With reference to FIG. 11, radio frequency identification tag 314 in accordance with still another alternate preferred embodiment is shown with like reference numerals indicating like elements as shown and described with respect to radio frequency identification tag 214. Thus, and as seen in FIG. 11, radio frequency identification tag 314 is formed by directly joining circuit chip 246 to an article 310 having an integrally formed antenna 222. Article 310 includes a substrate 316 that is formed with a locally compressed region 317 into which circuit chip 246 is positioned and secured to article 310. In this manner, circuit chip 246 is positioned slightly below surface 218 and is thereby protected from damage during use of article 310. It will be further appreciated that article 310 may be formed with the above described compressed region 317 and arranged to receive a circuit chip assembly, such as circuit chip assembly 12 or circuit chip assembly 112 described above. Once secured into

- 13 -

region 317, circuit chip 246 may be surrounded and/or covered by a potting material 360. Preferably the potting material is an ultraviolet curable polymer material that can be deposited over and around circuit chip 246 in region 317, and quickly cured by exposure to ultraviolet light.

- 5 A protective cover may also be employed and secured over circuit chip 246.

Radio frequency identification tag 514 is shown in FIG. 12 and includes a radio frequency identification tag circuit chip assembly 512 constructed in accordance with preferred embodiments of the present invention secured to substrate 516 within a recess 517. Recess 517 is formed as a compressed portion of substrate 516 to a depth sufficient that chip assembly 512 is disposed below a surface 518 of substrate 516. Formed on surface 518 is an antenna 522 including a first conductive portion 524 and a second conductive portion 526. Preferably antenna 15 522 is formed by print depositing a conductive ink onto surface 518. An anisotropic adhesive (not shown) is preferably used to bond chip assembly 512 within recess 517 such that chip assembly 512 electrically, and operably, couples to antenna 522. An accurately applied isotropic adhesive may also be used to bond and electrically couple chip assembly 20 512 without departing from the fair scope of the present invention. It will be further appreciated that chip assembly 512 may be a radio frequency identification tag circuit chip without departing from the fair scope of the present invention. Once chip assembly 512 is bonded into recess 517, a cover 560 is bonded to surface 518 and antenna 522 forming radio 25 frequency identification tag 514 having a thin, substantially flat configuration. In fact, the overall thickness of radio frequency identification tag 514 is not substantially greater than the thickness of chip assembly 512. It will also be appreciated that substrate 516 and cover 560 may comprise a portion of an article. For example, substrate 516 and 30 cover 560 may form a portion of a wall of a laminated package such as a cardboard box, label, envelope, ticket, waybill or the like.

Referring to FIG. 13, a radio frequency identification tag 614 includes a radio frequency identification tag circuit chip assembly 612 constructed in accordance with preferred embodiments of the present invention secured to substrate 616 within a recess 617. Recess 617 is 35

- 14 -

preferably formed as a compressed portion of substrate 616 to a depth of about one half the thickness of chip assembly 612, or in other words, such that an upper portion of chip assembly 612 is disposed above a surface 618. Formed on surface 618 is an antenna 622 including a first

5 conductive portion 624 and a second conductive portion 626. Preferably antenna 622 is formed by print depositing conductive ink onto surface 618. An anisotropic adhesive (not shown) is preferably used to bond chip assembly 612 within recess 617 such that chip assembly 612 electrically, and operably, couples to antenna 622. An accurately applied isotropic

10 adhesive may also be used to bond and electrically coupled chip assembly 612 without departing from the fair scope of the present invention. It will be further appreciated that chip assembly 612 may be a radio frequency identification tag circuit chip with departing from the fair scope of the present invention. Cover 660 is formed to include a cover

15 recess 662. Cover recess 662 is formed as a compressed portion of cover 660 to a depth of about one half the thickness of chip assembly 612 as measured from surface 664. Once chip assembly 612 is bonded into recess 617, cover 660 is bonded to surface 618 and antenna 622 with cover recess 662 registering with recess 517 and together forming radio

20 frequency identification tag 614 having a thin, substantially flat configuration. In fact, the overall thickness of radio frequency identification tag 614 is not substantially greater than the thickness of chip assembly 612. It will also be appreciated that substrate 616 and cover 660 may comprise a portion of an article. For example, substrate 616 and

25 cover 660 may form a portion of a wall of a laminated package such as a cardboard box, label, envelope, ticket, waybill or the like.

Referring to FIG. 14, a radio frequency identification tag 714 includes a radio frequency identification tag circuit chip assembly 712, constructed in accordance with preferred embodiments of the present

30 invention secured to substrate 716. Formed on an upper surface 718 of substrate 716 is an antenna 722 including a first conductive portion 724 and a second conductive portion 726. Preferably antenna 722 is formed by print depositing conductive ink onto surface 718. An anisotropic adhesive (not shown) is preferably used to bond chip assembly 712 to

35 surface 718 such that chip assembly 712 electrically, and operably,

- 15 -

couples to antenna 722. An accurately applied isotropic adhesive may also be used to bond and electrically coupled chip assembly 712 without departing from the fair scope of the present invention. It will be further appreciated that chip assembly 712 may be a radio frequency
5 identification tag circuit chip with departing from the fair scope of the present invention. Cover 760 is formed to include a cover recess 762. Cover recess 762 is formed as a compressed portion of cover 760 to a depth slightly greater than the thickness of chip assembly 712 as measured from surface 764. Once chip assembly 512 is bonded to
10 surface 718, cover 760 is bonded to surface 718 and antenna 722 with cover recess 762 surrounding chip assembly 712, thus forming radio frequency identification tag 714 having a thin, substantially flat configuration. In fact, the overall thickness of radio frequency identification tag 714 is not substantially greater than the thickness of chip
15 assembly 712. It will also be appreciated that substrate 716 and cover 760 may comprise a portion of an article. For example, substrate 716 and cover 760 may form a portion of a wall of a laminated package such as a cardboard box, label, envelope, ticket, waybill or the like.

In accordance with another aspect of the present invention, and
20 with reference to FIG. 15 and FIG. 16 a package container 410 suitable for use in a radio frequency identification tag system (not shown) includes an integrally formed antenna 422. FIG. 15 illustrates package container 410 in an unassembled state. Package container 410 includes a package medium 416 formed from a sheet of paper, cardboard or coated
25 cardboard material, with simple paper or cardboard providing a preferred, low cost medium. A plurality of cutouts 456 and a plurality of scores 458 are formed into package medium 416 allowing package medium 416 to be folded into a box shape 454 (FIG. 16) as is very well known in the art.

Formed on first surface 418 of package medium 416 is an antenna
30 422 including a first antenna element 424 and a second antenna element 426. Each of first antenna element 424 and second antenna element 426 are formed from a conductive material that is bonded or otherwise secured to, and thus integral to, package container 410. Most preferably, each of first antenna element 424 and second antenna element 426 are
35 formed by printing, using a suitable printable conductive medium. For

- 16 -

example, a carbon/graphite based conductive ink forms an effective antenna 422 when printed onto paper, cardboard and/or coated cardboard. Antenna 122 is shown to cover generally all of the available area of surface 418, and each of first antenna element 124 and second antenna element 126 include at a center portion of package medium 416, a first coupling region 428 and a second coupling region 430. Each of first coupling region 428 and second coupling region 430 are arranged to electrically couple a radio frequency identification tag chip assembly or a radio frequency identification tag circuit chip in accordance with the present invention.

A primary advantage that package container 410 provides is the substantial amount of antenna surface area. The area of antenna 422 is orders of magnitude larger than available in traditional radio frequency identification tags. Moreover, since antenna 422 covers substantially the entire interior surface 418 of package container 410, orientation sensitivity is greatly reduced. Antenna 422 may be printed using relatively inexpensive carbon/graphite bearing ink, and chip assemblies are added only as required, and when the package container 410 is assembled thereby reducing cost.

In summary, referring again to FIG. 1, there has been disclosed a radio frequency identification tag 14 including a radio frequency identification tag circuit chip 46 secured to an article 10. The article 10 is formed to include an antenna 22 and the radio frequency identification tag circuit chip 46 is electrically coupled to the antenna.

With reference to FIG. 2, the radio frequency identification tag circuit chip 46 may preferably comprise a radio frequency identification tag circuit chip assembly 12. The circuit chip assembly 12 includes a substrate 16 including a conductive pattern 37 and a radio frequency identification tag circuit chip 46 secured to the substrate 16 and coupled to the conductive pattern. The conductive pattern 37 is arranged to couple to the antenna 22 formed integral to the article 10.

Referring to FIG. 12, in another preferred embodiment of the present invention, a radio frequency identification tag 514 includes a substrate 516 formed to with a recess 517 in a surface 518 thereof and an antenna 522 formed on the surface. A radio frequency identification tag

- 17 -

circuit chip assembly 512 is secured within the recess and is electrically coupled to the antenna. A cover is secured over the surface.

Referring to FIG. 13, in still another preferred embodiment of the present invention, a radio frequency identification tag 614 includes a
5 substrate 616 formed to include a recess 617 in a surface 618 thereof and an antenna 622 formed on the surface. A radio frequency identification tag circuit chip 646 is secured within the recess and electrically coupled to the antenna. A cover 660 is secured over the surface, and the cover is formed to include a cover recess 662, and the cover recess arranged to
10 register with the recess.

Referring to FIG. 14, in yet another preferred embodiment of the present invention, a radio frequency identification tag 714 includes a substrate 716 having an antenna 722 formed on a surface 718 thereof. A radio frequency identification tag circuit chip assembly 712 is secured to
15 the surface and electrically coupled to the antenna. A cover 760 is secured over the surface, and the cover is formed to include a cover recess 762 with the cover recess arranged to surround the radio frequency identification tag circuit chip.

Referring to FIG. 15, another aspect of the present invention
20 provides a package container arranged for use in a radio frequency identification tag system including a package medium 416 and an antenna 422 formed on a surface 418 of the package medium.

Size and orientation limitations of radio frequency identification tag antenna are overcome in the present invention by forming the antenna as
25 part of an article to be tracked and securing to the article a radio frequency identification tag circuit chip assembly. The antenna is conveniently constructed by printing on a surface of the article with conductive ink. Radio frequency identification tag circuit chip assemblies are economically produced in mass.

30 Read ranges are increased by utilizing antenna of substantially larger area formed as part of the article.

Orientation sensitivity is reduced by forming the antenna on non-parallel surfaces of the article.

Radio frequency identification tag costs are reduced by forming the
35 antenna on the article using inexpensive conductive inks.

- 18 -

Inadvertent dislodging of the circuit chip assembly is avoided by providing a recessed area of the substrate into which the circuit chip assembly is secured and coupled to the antenna.

- 5 Many additional changes and modifications could be made to the invention without departing from the fair scope and spirit thereof. The scope of some changes is discussed above. The scope of others will become apparent from the appended claims.

We claim:

- 19 -

CLAIMS

- (1) An antenna arranged for use with a radio frequency identification tag circuit chip, the antenna comprising:
- 5 a substrate, the substrate forming a part of an article, and
a conductive pattern formed on the substrate, the conductive pattern including a first coupling region and a second coupling region for coupling the antenna to an interrogator, and the substrate having a locally compressed region about the first coupling region and the second
- 10 coupling region.
- (2) The antenna of claim 1, the article being one of a badge, a package, a container, and a label.
- 15 (3) The antenna of claim 1, the conductive pattern being a conductive ink printed on the substrate.
- (4) The antenna of claim 1, the first coupling region and the second coupling region electrically connected to a radio frequency identification tag circuit chip.
- 20 (5) The antenna of claim 1, the first coupling region and the second coupling region arranged for electrostatically coupling to an interrogator.
- 25 (6) The antenna of claim 1, the substrate comprising a first surface and a second surface, the first surface and the second surface being non-parallel and the conductive pattern being formed on the first surface and the second surface.
- 30 (7) A package container arranged for use with a radio frequency identification tag circuit chip, the package container comprising:
- a package medium, and
a conductive pattern formed on the package medium, the
- 35 conductive pattern including a first coupling region and a second coupling

- 20 -

region, for coupling the package to an interrogator and the package medium having a locally compressed region about the first coupling region and the second coupling region.

5 (8) The package container of claim 7, the conductive pattern forming an antenna for the radio frequency identification tag circuit chip.

(9) The package container of claim 7, the conductive pattern being a conductive ink printed on the package medium.



10

(10) The package container of claim 7, the first coupling region and the second coupling region electrically connected to a radio frequency identification tag circuit chip.



15 (11) The package container of claim 7, the first coupling region and the second coupling region arranged for capacitively coupling to an interrogator.



20 (12) A radio frequency identification tag comprising a substrate formed to include a recess in a surface thereof and an antenna formed on the surface, a radio frequency identification tag circuit chip secured within the recess and electrically coupled to the antenna, the antenna capacitively coupled to an interrogator and a cover secured over the surface.

25 (13) A radio frequency identification tag comprising a substrate formed to include a recess in a surface thereof and an antenna formed on the surface, a radio frequency identification tag circuit chip secured within the recess and electrically coupled to the antenna, the antenna electrostatically coupled to an interrogator and a potting material disposed
30 within the recess and surrounding the radio frequency identification tag circuit chip.



**FIG. 1****FIG. 2**



2/7

*FIG. 3**FIG. 4*

**FIG. 5****FIG. 6**

4/7

*FIG. 7**FIG. 8*



214




FIG. 11




FIG. 12




FIG. 13




FIG. 14





FIG. 16

INTERNATIONAL SEARCH REPORT

International application No.
PCT/US99/12640

A. CLASSIFICATION OF SUBJECT MATTER

IPC(6) :G08B 13/14

US CL :340/572.7,572.8

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

U.S. 340/572.7,572.8,825.31,825.34,693.5; 343/878,872

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched
NONEElectronic data base consulted during the international search (name of data base and, where practicable, search terms used)
NONE

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 5,528,222 A (MOSKOWITZ et al.) 18 June 1996, Fig. 6 and col. 5, lines 30-35.	1,2,4,7,8,10
A	US 5,382,952 A (MILLER) 17 January 1995.	1-13

☐ Further documents are listed in the continuation of Box C. ☐ See patent family annex.

	Special categories of cited documents		
"V"	document defining the general state of the art which is not considered to be of particular relevance	"T"	later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
"E"	earlier document published on or after the international filing date	"X"	document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
"L"	document which may throw doubts on priority claim(s) or which is used to establish the publication date of another citation or other special reason (as specified)	"Y"	document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art
	document referring to an oral disclosure, use, exhibition or other means		
	document published on or after the international filing date but earlier than the priority date claimed	"A"	document member of the same patent family

Date of the actual completion of the international search

15 JULY 1999

Date of mailing of the international search report

20 AUG 1999

Name and mailing address of the ISA/US
Commissioner of Patents and Trademarks
Box PCT
Washington, D.C. 20231

Facsimile No. (703) 305-3230

Authorized officer: *James R. Matthews*
THOMAS J. MULLEN, JR.

Telephone No. (703) 305-4382